

# Iridium Cavity Filter

## Antcom's P/N: 789-Iridium-N

### Size= 8.66inx4.5inx1.69in

ANTCOM CORPORATION . 367 Van Ness Way, Suite 602 . Torrance, CA 90501 . Tel: (310) 782-1076 . Fax: (310) 782-1086 . E-mail: [antennas@antcom.com](mailto:antennas@antcom.com) . <http://www.antcom.com>

Parameter	Unit	Specification
Center Frequency	MHz	1621.25
Frequency Range	MHz	1616 ~ 1626.5
IL (max)	dB	2.0 max
Return Loss in BW (min)	dB	16.0
Attenuation (min)	dB	35 @ 1614 MHz 25 @ 1628 MHz
Impedance (on all ports)	$\Omega$	50
RF Power Capability	W	20 W (max),
Connector	-	TNC(F) Material
Temperature Range	$^{\circ}\text{C}$ (deg.)	-10 ~ +60

